8 Port POE Switch

Functions

- 8 POE Port 10/100 Mbps
- 2 Port Uplink 1000 Mbps
- POE Support up to 150M
- 200 watt Power Supply
- 8 Gb Bandwidth
- Fanless
- Rackmount

MODEL	MNA-SW82G-P
Interfaces	
Total Port 12 Ports	Total Port 10 Ports (8 POE + 2 Uplink)
Max POE Output	Max POE Output 200 Watt
POE Port Control Texas Instruments Chipset	
Gigabit RJ45 POE Port	8 Port (Up To 30Watt Per Port)
Gigabit RJ45 Uplink Port	2
Gigabit SFP Port	-
Network Performance	
Standard	IEEE802.3x, IEEE802.3u, IEEE802.3az, IEEE802.3ab, IEEE802.3af, IEEE802.3at(Up to 30Watt
Protocols	CSMA/CD
Speed & Cabling	Ethernet 10Mbps (half duplex), 20Mbps (full duplex); 10BASE-T: 14,880bps/port Fast Ethernet 100Mbps (half duplex), 200Mbps (full duplex); 100BASE-TX:14,8800bps/port Gigabit Ethernet 1000Mbps (half duplex), 2000Mbps (full duplex); 1000BASE-TX: 1488000bps/port Cabling 10Base-TX:Cat 3 or above Cat.5 UTP(100m) POE=200M 100Base-TX:Cat 5 UTP(100m) POE=150M 1000Base-TX:Cat 6e UTP or Cat 6 UTP(120m) POE=150
Bandwidth	24Gb Internal Bandwidth
MAC Table	64Kb
Auto MDI-MDIX	Yes All Ports
Console	-
Hardware	
Processore Type	Realtek
LED Panel	POE Activity / Data Activity
PD`S	
IP Camera & IP Phone	Yes
General	
Dimension	438*330*45mm
Weight	4.9kg
Storage Temp	-20°C ~ +60°C / 10% ~ 90% RH
Operation Temp	-15°C ~ +50°C / 10% ~ 90% RH
Power	90~220VAC - 2.9A
MTBF	100K hrs min. MIL-HDBK-217F (25°)
Rackmount	Support
Radiation Electromagnetic	EN55016

دفتر مرکزی : تهران ، سهروردی شمالی ، خیابان دکتر قندی ، شماره ۱۱۶
ساختمان میکرونرم افزار
تلفن : ۷-۸۸۵۰۱۴۵۵ فاکس : ۸۸۷۶۹۵۲۱ (۰۲۱)
کارخانه : اتوبان تهران ساوه ، شهرک صنعتی پرند ، خیابان نارون
تلفن : 56417459 (21)

Micro Narm Afzar Industrial co.
Head Office: No.116 , MNA Building , Ghandi St.
North Shorevardi Ave. Tehran. Iran
Tel:+98(21) 88501455-7 Fax:88769521
Factory: C(34-35) Narvan St. Parand Industrial Town
Tehran saveh highway TEL ۵۶۴۱۷۴۵۹

mna@mna.ir www.mna.ir